

# SDL

## Lighting

### DMX 100

#### DMX 512 LED Controller



The DMX 100 is a purpose designed LED controller for use with our PX24500 DMX driver or any other DMX 512 driver. Colours and sequences are set using a small hand held RF remote control unit. It has built in pre set colours, cycle, and cross fade settings with variable speed.

#### Specifications

Voltage	12 V dc
Connections	RJ45 and 3 Pin XLR
Ambient Temperature	-20 to +50 Degrees Centigrade
Output	DMX 512
Control Interface	4 Button RF remote unit
Mounting	Surface
Dimensions	140mm x 80mm x 46mm