

# SDL

## Lighting

### PowerDriver 16



#### 16 LED Driver

PowerDriver 16 is a purpose designed LED driver capable of driving up to 16 Luxeon 1 Watt LED's. The Powerdriver 16 can drive wall washing, spot lighting or MR16 RGB Downlighter modules.

#### Specifications

##### Input

Voltage	195 – 255 V ac
Frequency	50 – 60 Hz
Power Factor	0.98
Efficiency	80%
Ambient Temperature	-20 to +85 Degrees Centigrade

##### Output

Output Current	350mA @ 100%
Output Voltage	10-54Vdc